



## VOLTAGE, CONTINUITY, AND CURRENT TESTER

# FLIR VT8™

The FLIR VT8 is a high-quality voltage, continuity, and current tester, ideal for electricians and service technicians who troubleshoot and verify electrical installations or systems within commercial and light industrial facilities. The FLIR VT8's optimized and open-jaw design allows it to fit into tight spaces and reliably measure large-diameter cables. Extensive measurement features make the FLIR VT8 a versatile tool – just one meter can get the job done. Carry the compact tester in your pocket to be ready at any moment for easy troubleshooting.

Choose from two models: the FLIR VT8-600 with a CAT III-600 V /CAT IV-300 V safety rating and a 100 A/600 V measuring range; or the FLIR VT8-1000 with the CAT III-1000 V/CAT IV-600 V safety rating and a 200 A/1000 V measuring range.

[www.flir.com/vt8-series](http://www.flir.com/vt8-series)



### RUGGED AND SAFE

Made with the quality and reliability you have come to expect from FLIR test and measurement tools

- Work more safely with the CAT IV safety ratings
- Safely store test leads when not in use with the built-in test lead holder
- Keep the test leads out of your way when you're not using them - the length is short enough to minimize interference, yet long enough to get the job done



### RICH FEATURES

Equipped with the capabilities you need for one versatile troubleshooting tool

- Measure AC/DC voltage and current, continuity, resistance, and capacitance
- Work efficiently in dimly lit areas using the bright LED worklight and backlight display
- Detect live AC voltages with the built-in non-contact voltage (NCV) detector
- Improve accuracy of readings with True RMS measurements



### FLEXIBLE, EASY TO USE

Designed for long, trouble-free operation so you can focus on the task at hand

- Take measurements in tight spaces with the optimized jaw design, and measure large-diameter cables with the wide jaw opening
- Operate the meter with one hand thanks to the compact, ergonomic design
- View information easily at any distance on the large multi-function LCD display

## SPECIFICATIONS

| Part Number                            | VT8-600  | VT8-1000                       |
|--|--|--------------------------------|
| <b>Electrical Measurement</b>          |  |                                |
| True RMS Voltage and Current           | Yes  |                                |
| Auto-Ranging                           | Yes  |                                |
| AC/DC Current Range                    | 100 A  | 200 A                          |
| AC/DC Current Resolution               | 0.1 A  |                                |
| AC (50 to 60 Hz) / DC Current Accuracy | ±2.5%  |                                |
| AC/DC Voltage Range                    | 600 V  | 1000 V                         |
| AC/DC Voltage Resolution               | 0.1 V  |                                |
| AC (45 to 66 Hz) / DC Voltage Accuracy | ± 1.5%, ±1.0%  |                                |
| Resistance                             | 60.00 MΩ ± (1.5%)  |                                |
| Continuity Check Threshold             | 10 Ω to 100 Ω  |                                |
| Capacitance                            | 600 μF ±4.0%, 6000 μF ±10.0%   |                                |
| Non-Contact Voltage Detector (NCV)     | ≥100 Vrms; ≤10 mm distance (LED/buzzer alerts)   |                                |
| Additional Measurement Functions       | DCA zero, relative mode (AC/DC voltage, AC current, and capacitance), data hold                          |                                |
| <b>General</b>                         |  |                                |
| Worklights                             | White LED  |                                |
| Jaw Opening                            | 15.5 mm (0.61 in)  |                                |
| Display                                | 6000-count backlit multi-function LCD  |                                |
| Display Rate                           | Approximately 3 times per second   |                                |
| Polarity                               | Automatic display of positive and negative polarity  |                                |
| Over-Range Indication                  | "OL" or "-OL" displayed  |                                |
| Auto Power Off                         | After 15 minutes   |                                |
| Power Source                           | 2 x AA alkaline batteries  |                                |
| Low battery Indication                 | Battery symbol is displayed when batteries need changing   |                                |
| <b>Environmental Data</b>              |  |                                |
| Operating Temperature                  | -10 to 50°C (14 to 122°F)  |                                |
| Relative Humidity                      | 95% max; 5 to 30°C (41 to 86°F) / 75% max; 30 to 40°C (86 to 104°F) / 45% max; 40 to 50°C (104 to 122°F) |                                |
| Storage Temperature                    | -30 to 60°C (-22 to 140°F), batteries not installed  |                                |
| Drop Test                              | 2 m (6.6 ft)   |                                |
| <b>Physical Data</b>                   |  |                                |
| Dimensions: (W × H × D)                | 210 mm × 53 mm × 35 mm (8.27 in × 2.1 in × 0.67 in)  |                                |
| Weight                                 | 163.7 g (5.7 oz) including batteries   |                                |
| <b>General Information</b>             |  |                                |
| Warranty                               | Limited 3-year   |                                |
| Certifications                         | C-UL-US, CE, RCM   |                                |
| Safety Category Rating                 | CAT IV-300 V<br>CAT III-600 V  | CAT IV-600 V<br>CAT III-1000 V |
|  | EN 61010-1<br>EN 61010-2-032<br>EN 61010-2-033   |                                |

Specifications are subject to change without notice. For the most up-to-date specs, go to [www.flir.com](http://www.flir.com)

**CORPORATE HEADQUARTERS**  
FLIR Systems, Inc.  
27700 SW Parkway Ave.  
Wilsonville, OR 97070  
PH: +1 877.773.3547

**LATIN AMERICA**  
FLIR Systems Brasil  
Av. Antonio Bardella, 320  
Sorocaba, SP 18085-852  
Brasil  
PH: +55 15 3238 7080

**NASHUA**  
FLIR Systems, Inc.  
9 Townsend West  
Nashua, NH 03063  
USA  
PH: +1 866.477.3687

**CANADA**  
FLIR Systems, Ltd.  
3430 South Service Road,  
Suite 103  
Burlington, ON L7N 3T9  
PH: +1 800.613.0507

[www.flir.com](http://www.flir.com)  
NASDAQ: FLIR

Equipment described herein is subject to US export regulations and may require a license prior to export. Diversion contrary to US law is prohibited. Imagery for illustration purposes only. Specifications are subject to change without notice. ©2018 FLIR Systems, Inc. All rights reserved. Rev 03/19

18-1885-INS



The World's Sixth Sense®

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Extech:](#)

[VT8-600](#) [VT8-1000](#)